

Функция	Parameter Write=1	Режим применения	Комбинация клавиш	
Resetting OT alarm		При включении питания ЧПУ	<P> + CAN	
Memory all clear		o	RESET + DELETE	
Parameter/offset clear	o	o	RESET	
Clearing All program	o	o	DELETE	
Clear protect password program			<O> + <M>	
Program under edition at power off(PS101)		o	PROG + RESET	
PMC RAM LADDER		o	<X> + <O>	
PMC parameter clear		o	<O> + <Z>	
Pass startup MGI and C-EXE		o	<M> + <O>	
Stop startup LADDER		o	CAN + <Z>	
Additional SRAM area clear		o	<O> + DELETE	
Resetting alarm 100		x	CAN + RESET	
Screen switching between NC and loader			SHIFT + HELP	
Skip servo		o	<N> + <S>	
IPL Monitor			<-> + <.>	
Ignore work hours			CAN + <X>	